

Installation and Removal Instructions for the macOS Printing Dialog Extension

Installation and Removal Instructions for the macOS Printing Dialog Extension Release 10

This ReadMe file contains instructions for installing the Printing Dialog Extension (PDE) on macOS systems. PDE is the standard Printing Dialog Extension that adds additional printer feature selections. The PDE can be installed on macOS Mavericks (version 10.9) and later.

The DigimasterDriver_release.pkg is a single install package.

The package installs all the required software on your computer (both the Filter and the PDE).

The DigimasterDriver_release.pkg package is the extension to the standard macOS Print window, which includes additional printing options for your printer. The installer supports a multi-language installation. When you log into the operating system, the user interface will display in your preferred language. If this release does not support the selected preferred language, the default language is English.

Before proceeding, verify with your macOS administrator that you have the appropriate privileges to install the PDE.

NOTE: The terms used in the installation steps are valid for macOS 10.9 and later. If you are installing on a different macOS version, the terms may be slightly different.

Installation and Removal Instructions for the macOS Printing Dialog Extension

To install the Printing Dialog Extension on macOS:

NOTE: Is it not necessary to remove a previous version of the driver before installing a new version of the driver.

1. Launch DigimasterDriver_release.pkg and follow the instructions in the installer.
2. From the *Apple* menu, select *System Preferences*.
3. Select *Printer and Scanners*.
4. Select the plus (+) sign and select *IP* when "Add" window appears.
5. From the *Protocol* menu, select *Line Printer Daemon - LPD*.
6. In the *Address* field, type the IP address of the printer. You can find the IP address at the printer.
7. In the *Queue* field, type the actual Print Server queue name on the printer. You can find the queue name by checking the Print Server on the SCS. Not entering a queue name can result in jobs not being sent to the printer.
8. From the *Print Using* list, select *printing software*.
9. From the *Printer Software* search fields, type the brand name. For example, *Kodak*.
10. From a list of printers, select <Brand><Model><Version>PPD. For example, *Kodak Digimaster 10.0 PPD*.

11. Click *Add*.

The printer appears in the *Printer List* window.

Installation and Removal Instructions for the macOS Printing Dialog Extension

To remove the printing dialog extension:

To completely remove the driver from your system, you will need to delete all of the files in all of the locations indicated below:

- Paper Catalog

- Delete the /<company name>/<product name> folder located in /Library/Application Support.

- Printer Driver

- Delete the <product code>.bundle file located in /Library/Printers/<company name>/<productname>.

- PPD

- Delete the <product code>_xx.PPD file located in /Library/Printers/PPDs/Contents/Resources/xx.lproj, where xx is a 2 character code indicating the language.

- Receipt

- Delete the <company name product name>.pkg file found in /Library/Receipts.

-

- Filter

- Delete the filter file located in /usr/libexec/cups/filter/<company name>/<product name>.